

i-tec Universal USB-A/USB-C/Thunderbolt, Quattro 4K Display Docking Station + Power Delivery 100W

i-tec Universal USB-A/USB-C/Thunderbolt, Quattro 4K Display Docking Station + Power Delivery 100W



PRODUCT DESCRIPTION

Maximum performance docking station. Supports up to four external monitors at 4K/60Hz or 2x 5K/60Hz. The perfect product for users who require multiple monitors without compromising on image stability, resolution and refresh rate. The dock also features a USB-C fast charging port (with up to 30W charging power), especially for charging smartphones and tablets, fast USB ports, a 2.5 Gbps LAN port, as well as other peripherals. The dock can be connected to virtually any laptop, regardless of make, model or operating system type. Any USB port (3.1 Gen. 1, USB-C or Thunderbolt" 3 or 4) is sufficient. The dock can be installed behind the monitor (if it supports a standard VESA mount), using the i-tec VESA mount.

- Support for up to 4 external monitors with resolutions up to 4k/60 Hz (or 2 x 5k/60 Hz)
- 4x HDMI and 4x DP ports
- USB-C charging port for smartphones and tablets (30W)
- Ultra-fast Gen2 USB-C port with data transfer speeds up to 10 Gbps
- 3x USB-A 3.1 Gen. 1
- LAN port with up to 2.5 Gbps (10/100/1000/2500 Mbit)
- 3.5 mm audio/mic port
- 1x SD/microSD slot
- Laptop power supply up to 100 W
- Docking station on/off button
- Support for installation behind a monitor

PRODUCT FEATURES

- 1x USB-C port for connection to USB-C or USB-A 3.1 Gen. 1 devices (connecting cable USB-C and USB-C to USB-A 3.1 Gen. 1 adapter included)
- Docking Station Technology: DisplayLink (DL-6910)
- Power Delivery: 100 W
- Video Ports: Up to 4 active displays at the same time.
 - 4x HDMI
 - 4x Display Port (DP++ supported)
- Resolution:
 - \circ 2 monitors 4x DP → up to 2x 5K/60Hz*
 - \circ 4 monitors 4x HDMI or 4x DP \rightarrow up to 4x 4K/60Hz
- 1x USB-C port (for power only) supporting Power Delivery up to 30W



- 1x USB 3.1 port (10Gbps) supporting Fast Charge (BC 1.2)
- 3x USB-A 3.1 Gen. 1 port (5Gbps)
- 1x Ethernet RJ-45 2.5Gbps port (RTL8156)
- 1x 3.5mm combined audio and microphone input
- 1x SD/microSD slot
- 1x power input (DC 20V/9A)
- MAC Address cloning: Yes (using i-tec Docker Pro software)
- WOL: S1, S2, S3
- ON/OFF button to turn the docking station on and off
- LED indication
- Support for Kensington lock
- Support for VESA mounting
- OS: Windows 10 / 11, macOS, Android 5 or later, Chrome OS R51 or later, Linux Ubuntu
- Product dimensions: 245 x 98 x 37 mm
- Product weight: 592 g
- Package dimensions: 280 x 130 x 111 mm
- Package weight: 1726 g

Hardware Requirements:

• Device with a free USB-A, USB-C, USB4 or Thunderbolt™ 3/4 port

Power Delivery Requirements:

• Device with a free USB-C, USB4 or Thunderbolt™ 3/4 port with Power Delivery support

Video Output Requirements:

Device with a free USB-C or USB4 port with DisplayPort Alternate Mode support or a Thunderbolt™ 3/4 port

Operating System:

• Windows 10 / 11, macOS, Android 5 or later, Chrome OS R51 or later, Linux Ubuntu

SPECIFICATION

Part Number	Product Description & EAN
CAQUATTRODOCKPDPRO	i-tec Universal USB-A/USB-C/Thunderbolt, Quattro 4K Display Docking Station + Power Delivery 100W EAN: 8595611704161
CAQUATTRODOCKPDPROUK	i-tec Universal USB-A/USB-C/Thunderbolt, Quattro 4K Display Docking Station + Power Delivery 100W EAN: 8595611704826
Hardware	
Bus type	USB-C, USB-3.1
System Requirements	
Operating system	Windows 8 / 8.1 /10 Windows 10/11 macOS X Android 5 or later Linux Ubuntu 14.04, 16.04, 17.04, 17.10, 18.04, 19.04 Chrome OS R51 or laterWindows 10 - Automatic installation of OS

^{* 5}K resolution is supported only by Windows



	drivers. Other operating systems - manual driver installation. Firmware updates automatically.
Other features	
Colour	black
Housing Material	ABS
Product Dimensions	245 x 98 x 37 mm
Product Weight	592 g
Package Weight	1726 g
Packaging Dimensions (LxWxH)	280 x 130 x 111 mm
Support	
Warranty period	2 years
Technical support	lifetime
Package contents	
Product	
USB-C cable with USB-C to USB-A adapter (100 cm)	
Power adapter	
Quick Start	

For further information regarding setup or for answers to FAQ's, please visit our website $\underline{\text{i-tec.pro}}$. Specifications are subject to change without notice.

Updated 21.9.2023